Circuit Breakers



Blue Star Power Systems, Inc's MC (Molded Case) Series Circuit Breakers are the highest quality in the industry. They will protect the power system and corresponding equipment from damaging fault currents circuits and overloads.

80% Rated Circuit Breakers

80% rated breakers can only be applied continuously at 80% of the rated breaker. Tripping of the circuit breaker if the current goes above 80% will depend on the amount of current and the duration.

100% Rated Circuit Breakers

100% rated breakers can be applied at 100% of their current rating continuously.

Accessories

Shunt Trip - Provides a means of tripping the circuit breaker from a remote source by energizing a solenoid in the breaker. This can be achieved through the panel faults such as engine shutdowns, overcurrent, etc. The circuit breaker will have to be reset locally in the event of a tripped breaker.

Bell Alarm / Alarm Switch - Provides remote indication of whether the circuit breaker is in a tripped position. The bell alarm will remain unchanged during on-off operations and during operation by the Push-to-Trip button on the circuit breaker.

Auxiliary Switch/Contacts - Provides remote indication of whether the circuit breaker is in an open or closed state.

Ground Fault Indication/Alarm - Adjustable relay that indicates a ground fault condition with adjustable time delay.

Trip Unit

LI Breakers - Includes adjustable Long-Time pickup and delay and adjustable Instantaneous pickup. LSI Breakers - Includes features of LI Breakers with addition of Short-Time pickup and delay.

Breaker Model	Amperage	Percentage Rated	Maximum Voltage Rating (AC)	UL Listed Interrupting Rating (kA)			Lug Qty. and Size (Cu & Al)
				240	480	600	
H-Frame	15-150	80% or 100%	600	25	18	14	(1) #14-3/0
Q-Frame	70-250	80%	240	10	-	-	(1) #4-300 kcmil
J-Frame	150-175	80% or 100%	600	25	18	14	(1) #4-4/0
	200-250						(1) 3/0-350 kcmil
L-Frame	125-400	80% or 100%	600	65	35	18	(2) 2/0-500 kcmil
	200-600	80%	600				
M-Frame	300-800	80%	600	65	35	18	(3) 3/0-500 kcmil

Breaker Model	Frame Size	Percentage Rated	Maximum Voltage Rating (AC)	UL Listed Interrupting Rating (kA)			Lug Qty. and Size (Cu & Al)
				240	480	600	
P-Frame	600	- 80% or 100%	600	65	35	18	(3) 3/0-500 kcmil
	800						
	1000						(4) 3/0-500 kcmil
	1200						
R-Frame (LSI Standard)	1600	- 100%	600	65	35	18	(12) 3/0-750 kcmil
	2000						(15) 3/0-750 kcmil
	2500						(18) 3/0-750 kcmil
	3000						(21) 3/0-750 kcmil

